Honeywell
THE POWER OF CONNECTED | Farenhyt™ Series

WIDP-PULL-DA

SWIFT Wireless Pullstation

The Honeywell® SWIFT® addressable pull station is a dual-action, manual pull station with a key-lock reset feature that provides one addressable alarm initiating input. The pull station features similar aesthetic design and durable construction characteristics as the wired counterpart to blend seamlessly throughout the environment. The device communicates to the FACP through the SWIFT mesh network and gateway, and is powered by 4 batteries offering a 2-year, UL listed battery life.



Installation is fast and straightforward by using a mounting plate that can be surface mounted. Once the mounting plate is firmly attached to the wall, the pull station is snapped into place and locked down with 3 screws.

The mechanical operation is simple and easy to use in an emergency with a PUSH IN/PULL DOWN handle that latches in the down position to clearly indicate the station has been operated while the word "ACTIVATED" appears on top of the handle in bright yellow, further indicating the operation of the station.

The wireless pull station meets the Americans with Disabilities Act Accessibility Guidelines' (ADAAG) controls and operating mechanisms guidelines (section 4.1.3[13]) and the Americans with Disabilities Act (ADA) requirement for a 5-pound maximum pull force to activate the pull station and conforms to ANSI/UL Standard 38.

The SWIFT wireless system offers intelligent (addressable) devices which provide secure, reliable communication to the Fire Alarm Control Panel (FACP) across a Class A mesh network. Wireless devices create an opportunity for applications where it is costly (concrete walls/ceilings, buried wires), obtrusive (surface mount conduit), or possibly dangerous (asbestos) to use traditional wired devices. In addition, both wired and wireless devices can be present on the same FACP providing an integrated wired-wireless solution for increased installation potential.

FEATURES & BENEFITS

- Easy, fast, wireless installation
- Participates in a Class A mesh network
- Maintenance personnel can open station for inspection and address setting without causing an alarm condition
- Built-in tri-color LED flashes in normal operation and latches steady red when in alarm
- Handle latches in down position and the word "ACTIVATED" appears to clearly indicate the station has been operated
- Standard "code wheel" for setting the SLC address
- For use in commercial applications
- Smooth dual-action design
- Highly visible
- Meets ADAAG controls and operating mechanisms guidelines (Section 4.1.3[13]); meets ADA requirement for 5lb. maximum activation force
- Meets UL 38, Standard for Manually Actuated Signaling Boxes
- Made of durable polycarbonate material
- Attractive shape and textured finish
- Key reset
- Includes Braille text on station handle

The mesh network within the SWIFT system creates a child-parent relationship between the devices so that each device has two parents providing a second path for communications on every device. If one device can no longer operate for any reason, the rest of the devices can still communicate with each other, directly or through one or more intermediate devices. Once an initial mesh network is formed, mesh restructuring automatically occurs to find the strongest paths possible within the network.

The SWIFT system also engages frequency hopping to prevent system interference whether intentional or accidental. Each device complies with part 15 of the FCC rules meaning operation is subject to the following two conditions: 1) The device may not cause harmful interference and 2) The device must accept any interference received including interference that may cause undesired operation.

Compatible Control Panels

- IFP-75
- IFP-300
- IFP-300ECS
- IFP-2100
- IFP-2100ECS
- RFP-2100

SWIFT Components and Ordering Information

- **WIDP-PULL-DA:** Wireless addressable pullstation. Requires (4) CR-123A batteries (included).
- **WIDP-WGI:** Wireless SWIFT Gateway - 1 SWIFT Gateway is required for each wireless mesh, and supports up to 49 SWIFT detectors or modules. Connects to the SLC loop of a compatible panel using IDP protocol. Power may be supplied by the SLC circuit or via an optional 24VDC input.

Note: Use of the 24VDC input may be more convenient for service as it allows for powering down a gateway without shutting down an SLC loop.

- **WIDP-PHOTO:** Intelligent, wireless photo detector. Requires one B210W base for installation. Requires (4) CR-123A batteries (included).
- **WIDP-ACCLIMATE:** Intelligent wireless Acclimate® heat and photo detector using combined heat and smoke sensor information and the ability to automatically adjust sensitivity based on ambient changes in the environment. Requires one B210W base for installation. Requires (4) CR-123A batteries (included).
- **WIDP-HEAT-ROR:** Intelligent wireless rate of rise (135°) heat detector. Requires one B210W base for installation. Requires (4) CR-123A batteries (included).
- **WIDP-HEAT**: Intelligent wireless fixed-temperature (135°) heat detector. Requires one B210W base for installation. Requires (4) CR-123A batteries (included).
- **WIDP-MONITOR:** Wireless monitor module. Used to monitor devices with mechanical contact actuation. Includes a special cover with a built- in tamper magnet. Recommended for installation in a SMB500-WH box (ordered separately) rather than a metal backbox for best performance. Requires (4) CR-123A batteries (included).
- **WIDP-RELAY:** Wireless relay module for use with the WIDP-WGI wireless gateway. Includes a special cover with a built-in tamper magnet. Recommended for installation in an SMB500-WH box (ordered separately) rather than a metal backbox for best performance. Requires (4) CR-123A batteries (included).
- **WAV-CRL, WAV-CWL:** SWIFT Wireless Addressable AV bases. Requires (8) CR-123A batteries (included). Requires a non-compact ceiling System Sensor® L-series notification device (ordered separately).
- **W-SYNC:** Wireless sync module. Requires (4) CR-123A batteries (included).
- **SMB500-WH:** Optional surface-mount backbox.
- **B210W:** Detector base used for wireless detectors. Includes a built-in magnet so that wireless devices can establish installed and tampered states.
- **SWIFT Tools:** Programming and diagnostic utility. Free download from www.farenhyt.com. For installation on a (typically laptop) PC running an approved version of Windows (See Minimum System Requirements for SWIFT Tools). Requires the W-USB radio/ antenna dongle for communication with SWIFT Wireless devices.
- **W-USB:** Wireless USB radio/antenna dongle that plugs into the USB port of a PC running SWIFT Tools. The W-USB provides a communication link with SWIFT Wireless devices that are within approximately 20 feet and have not formed a mesh. Alternately, when the devices have formed a mesh, bringing the PC/W-USB within range (20 ft.) of the gateway for that mesh will allow SWIFT Tools to acquire information on all devices in that mesh, including point-to-point signal strength for all links.
- **W-BATCART:** Wireless battery cartridge, 10-pack. For use with wireless pullstations and AV bases.

WIDP-PULL-DA Technical Specifications

Maximum Transmit RF Power: 17 dBm
Radio Frequency Range: 902-928 MHz
Temperature Range: 32°F to 120°F (0°C to 49°C)
Humidity: 10% to 93% Non-condensing
Battery Type: 4 Panasonic® CR123A or 4 Duracell® DL123A
Battery Life: 2 year minimum
Battery Replacement: Upon TROUBLE BATTERY LOW display and/or during annual maintenance
Dimensions: 5.6" (142 mm) H x 4.2" (107 mm) W x 2.1" (53 mm) D

AGENCY LISTINGS AND APPROVALS

The listings and approvals below apply to the WIDP-PULL-DA. In some cases, certain modules may not be listed by certain approval agencies or listing may be in process. Consult factory for latest listing status.
UL Listed: S6012
CSFM: 7150-0559:0513
FM Approved
FDNY: COA #6245, #6248, #6251
FCC ID: AUBWFSPS

Acclimate® Plus, Honeywell®, System Sensor®, and SWIFT® are registered trademarks,and Farenhyt™ is a trademark of Honeywell International Inc. Microsoft® and Windows® are registered trademarks of Microsoft Corporation. Duracell® is a registered trademark of Duracell U.S. Operations Inc. Panasonic® is a registered trademark of Panasonic Corporation. ©2018 by Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited.

This document is not intended to be used for installation purposes. We try to keep our product information up-to-date and accurate. We cannot cover all specific applications or anticipate all requirements. All specifications are subject to change without notice.

Country of origin: Mexico

Honeywell Fire Solutions
12 Clintonville Road
Northford, CT 06472-1610
203.484.7161
www.farenhyt.com

FH-61058 | B | 10/18
©2018 Honeywell International Inc.

Honeywell